

XK3192-BC



The XK3192-B digital dynamometer has stable performance and can be easily set, checked, programmed and calibrated. It has the advantages of high product adaptability and easy operation.

Analog input and A/D	
Accuracy	C3
A/D switch mode	Σ - Δ
A/D switch speed	10 times / second
A/D resolution	500000 max
Load cell excitation	5V, ,max 100mA (8 pcs of 350 Ω load cells)
Working environment and safety performance	
Power supply	AC220V,50 \pm 1Hz
Working temperature	-10 $^{\circ}$ C to +40 $^{\circ}$ C
Storing temperature	-30 $^{\circ}$ C to +75 $^{\circ}$ C
Cover	ABS
Weight	About 1kg
Outside dimension	220mm x 140mm x 125mm
Built-in battery	DC6V/4AH battery
Features	
1	Digital calibration
2	High precise A/D switch
3	Port: RS232